

Syscompact 4000

BAUR cable fault location system



The figure is illustrative.

Compact and multifunctional

- Precise and dependable cable fault location
- High-performance surge voltage generator
- Precise fault location methods for every type of fault

The compact cable fault location system, Syscompact 4000, is used for the pre-location and pin-pointing of faults on low- and medium-voltage cables.

Thanks to the novel operational concept and the integrated location methods, cable fault location with Syscompact 4000 is faster and easier. The high-performance industrial PC and improved measurement parameters allow for a precise cable fault location in all cable types.

The system can be equipped with different surge voltage generators SSG 1100, SSG 1500* or SSG 2100*. The surge voltage generators have an automatic surge mode, thereby also allowing the Syscompact 4000 to be used for acoustic pin-pointing.

Thanks to its compact design, the Syscompact 4000 is easy to transport and is also suitable for installation in any small van with a payload of 300 to 500 kg.

Functions

- Insulation resistance measurement up to 1,000 V*
- TDR: Time Domain Reflectometry
- Envelope curve display for intermittent faults – even small changes in impedance are made visible and saved.
- SIM/MIM: secondary/multiple impulse method with surge voltage or in DC mode
NEW: 20 reflection measurements per HV pulse
- ICM: impulse current method with surge voltage or in DC mode
- Surge mode for acoustic pin-pointing
- DC voltage testing
- Cable sheath testing

Features

- Easy operation thanks to the intuitive operational concept
- Integrated proven cable fault pre-location methods
- Automatic detection of cable end and fault position
- Dynamic input signal gain
- Automatic saving of all measurement data
- Storage for more than 100,000 measurements
- Interface to GIS databases*
- Modular system, easily expandable for cable testing and diagnostics

* Option

Technical data

IRG 4000 time domain reflectometer	
Pulse voltage	TDR 20 – 200 V
Pulse width	20 ns – 1.3 ms
Voltage-proof up to	400 V, 50/60 Hz
Output impedance	8 – 2,000 Ohm
Input signal gain	Dynamic range 107 dB (-63 to +44 dB)
Display range	10 m – 1,000 km (at v/2 = 80 m/μs)
Accuracy	0.1% relating to the measurement result
Data rate	400 MHz
Resolution	0.1 m (at v/2 = 80 m/μs)
Velocity of propagation (v/2)	20 – 150 m/μs, adjustable
Measurement modes	<ul style="list-style-type: none"> ▪ Automatic measurement mode ▪ Differential measurement ▪ Mean value calculation ▪ Continuous measurement ▪ Stop after recording the change ▪ Envelope curve display for the location of intermittent faults
Storage capacity	> 100,000 measurements (hard disk limit)
Display	TFT monitor acc. to offer
User interface languages	user interface available in 22 languages
Data export format	PDF
GIS interface (option):	Export/import GIS data
Data synchronisation	USB
BAUR GeoBase Map (option)	Full version

Insulation resistance measurement	
Voltage	up to 1,000 V
Measurement range	0 ohm – 5 Gohm

Surge voltage generator	
Surge voltage ranges	0 – 8 kV, 0 – 16 kV, 0 – 32 kV
Surge energy SSG 1100	1,100 J with option SZ 1550: 1,400 J with option SZ 2650: 2,470 J
Option SSG 1500	1,540 J with option SZ 1550: 1,460 J with option SZ 2650: 2,530 J
Option SSG 2100	2,050 J with option SZ 1550: 1,580 J with option SZ 2650: 2,660 J
Surge sequence	10 or 20 pulses/min, single surge
Option SSG 1500	20 or 30 pulses/min, single surge
DC voltage	0 – 32 kV
Max. output current (in DC mode)	560 mA (0 – 8 kV)
Option SSG 1500/SSG 2100	850 mA (0 – 8 kV)

System	
Power supply	220 – 230 V, 50/60 Hz
Options	<ul style="list-style-type: none"> ▪ 110 – 120 V, 50/60 Hz (with external auto transformer) ▪ 240 V, 50/60 Hz (with conversion kit for mains supply)
Ambient temperature	0°C to +50°C
extended temperature range*	-20°C to +60°C
Storage temperature	-40 to +60°C
Dimensions (W x H x D)	Approx. 935 x 1,145 mm x 775 mm (incl. KTG M3 cable drum rack)
Weight	From 195 kg (depending upon equipment)
Degree of protection	IP22
Safety and EMC	CE-compliant in accordance with Low Voltage Directive (2014/35/EU), EMC Directive (2014/30/EU), EN 60068-2-ff Environmental testing

* Limitation of performance data possible

Standard delivery

BAUR Syscompact 4000 cable fault location system:

- IRG 4000 time domain reflectometer
- Uninterruptible power supply (UPS)
- PC keyboard
- Measuring cable (3 m)
- SA 32 SIM/MIM coupling
- SSG 1100 surge voltage generator
- SK 1D inductive coupling for ICM
- 19" rack, height 27 RU (1,200.15 mm), depth 700 mm
- KTG M3 Cable drum rack with HV connection cable, mains supply cord and earth cable (incl. earth terminal), each 25 m
- Jumper plug for external emergency off unit
- CS 2 HV coaxial connection socket, 40 kV
- GR 40 earth rod
- User manual

Options

- Insulation resistance measurement
- BAUR GeoBase Map
- Interface for GIS data export/import
- Surge voltage generator SSG 1500 instead of SSG 1100
- Surge voltage generator SSG 2100 instead of SSG 1100
- SZ 1550 surge capacitor extension
- SZ 2650 surge capacitor extension
- protrac® pin-pointing system / "Acoustics" set
- GDR 40-250 discharge and earth rod
- KTG M3 cable drum rack with HV connection cable, mains supply cord and earth cable, each 50 m
- Trolley for Syscompact 4000
- Steel frame with wheels and guide rods
- Steel pallet for Syscompact 4000
- TDR connection cable, 3-phase, 25 m, on hand cable drum
- TDR connection cable, 3-phase, 50 m, on hand cable drum

Options for power supply

- Conversion kit for 240 V mains supply for SSG 1100
- Conversion kit for 240 V mains supply for SSG 1500/SSG 2100
- External auto transformer 110/230 V, 1.5 kVA, for SSG 1100
- External auto transformer 110/230 V, 3.0 kVA, for SSG 1500/SSG 2100

Contact:

BAUR GmbH (Headoffice Österreich)
T +43 (0)5522 4941-0
F +43 (0)5522 4941-3
headoffice@baur.at
www.baur.eu

BAUR Prüf- und Messtechnik GmbH
T +49 (0)2181 2979 0
F +49 (0)2181 2979 10
vertrieb@baur-germany.de
www.baur-germanv.eu

BAUR France
T +33 (0)9 800 10 300
F +33 (0) 172 718 485
info@baur-france.at
www.baur.eu/fr

Baur do Brasil Ltda.
T +55 11 297 25 272
atendimento@baurdobrasil.com.br
www.baurdobrasil.com.br

奥地利保尔公司上海代表处
电话 +86 (0)21 6133 1877
传真 +86 (0)21 6133 1886
shanghaioffice@baur.at
www.baur.eu/china

BAUR Test Equipment Ltd. (UK)
T +44 (0)20 8661 957
sales@baurtest.com
www.baurtest.com

BAUR Representative Office Hong Kong
T +852 2780 9029
F +852 2780 9039
office.hongkong@baur.at
www.baur.eu

BAUR representatives:
www.baur.eu/en/baur-worldwide

